


# Optimum M4240




## Bluetooth Access Point Installation

Bluetooth wireless technology is a short-range communications technology intended to replace the cables connecting portable and/or fixed devices while maintaining high levels of security. Hypercom's Bluetooth access points provide centralized communications for the Optimum M4240 terminal and are readily available in two versions: AP100 V.90 Dial or AP110 Ethernet. Each access point has a wireless range support of up to 100 meters or 328 feet, in a direct line of sight and can communicate simultaneously with up to seven Optimum M4240 terminals.



Remove access point, cables & screws from the box. Choose the best location to place/mount the access point (wireless range supports up to 100m/328ft).


Note: Ensure the AC Power Adapter reaches a 110-volt or regional grounded power receptacle. For AP100 Dial Access Point, ensure that the RJ11 telephone cable reaches a telephone wall jack. For AP110 Ethernet Access Point, ensure that the Ethernet cable reaches the Internet device.



Rear panel displays labeled ports (as shown):


- **POWER** port = AC Power Adapter & Power Cord
- **SERIAL** port = RS232 Cable (not included)
- **LINE\*** port = RJ11 Cable / **NET\*** port = Ethernet Cable

\*Note: AP110 Ethernet Access Point will display NET port (instead of LINE port).



Securely connect one end of your telephone cable into the blue port labeled LINE on the back of the Access Point. Connect the other end into the telephone wall jack.

Note: For AP110 Ethernet Access Point, connect one end of your Ethernet cable into the white port labeled NET, then connect the other end into your internet device. Follow manufacturer's instructions when setting up your internet device.



Plug the power cord connector into the red port labeled POWER, then plug the AC Power Adapter into 110-Volt or regional grounded power receptacle. Pair an Optimum M4240 terminal with the access point. For detailed instructions, see the *Optimum M4200 Family Hardware & Installation Guide (Pair Bluetooth Terminal with Access Point)*.

### World Headquarters:

Hypercom Corporation | 8888 E. Raintree Dr., #300, Scottsdale, AZ 85260 USA

Tel: +1.480.642.5000 | Fax: +1.480.642.4655 | [www.hypercom.com](http://www.hypercom.com)

© 2007, Hypercom Corporation. All rights reserved.

940546-004 Rev. A 01/08

